

HDb2800 Series

HDMI 1080p Encoder/ RF Modulator



For organizations looking to encode and modulate HDMI sources cost-effectively, the HDBridge 2800 Series is a great option. This four channel encoder/ modulator allows you to deliver HD video up to 1080p resolution to an unlimited number of displays over almost any distance.

The HDbridge 2800 series converts high definition AV sources into an RF signal received a television's QAM (NA model) or DVB-T/C (EU model) digital tuner over coax cable. With its high 45 dBmv RF output, you can send your content to an unlimited number of displays over nearly any distance.

SUPERIOR VIDEO QUALITY

- Full MPEG-2 implementation
- I, P, and B Frames
- Low latency
- Full motion estimation with a wide search range

EXTENSIBLE ARCHITECTURE

- Easy downloadable firmware updates
- Future enhancements provided regularly
- Emergency Alert System (EAS)

Multiple units can be combined to create a headend that supports over 100 channels on the RF network. This unit is designed primarily for high channel density environments where rapid deployment, advanced management, and compatibility are critical.

MODELS:

HDb2840-NA

4 HDMI inputs for up to 1080i/1080p component/VGA

HIGH RELIABILITY

- Low-stress power system
- Full system instrumentation and monitoring
- Official international regulatory approval
- Forced air cooling for effective thermal control

EASE OF MANAGEMENT

- Powerful, highly intuitive web interface
- On-site or remote management
- Configure/manage multiple units from front Panel Display for local management

Zv	Headend: Unname	d, No location Edit		User Name: admin Logo	ut	Send Emergency Alert	Maestro
Status	Channel Plan	AV Source R	F Device N	etwork ZvShow	STB EAS Config	Admin Support About	
48 connected Manage All No settings have been changed from their active values.							
System Auto-name	Slot AV Po	rt Enabled RF# Set All V Set All	Channel # Name ▼ Set All ▼ Set All ▼	Long Name Rating Set All V Set All V			
✓ 4_support_4 🥼	2vsho	w Enabled 💌 38	≯ 38.2 ≯ 2840-sh	2840-1 TV-G ¥ 2840-show TV-G ¥			
	2 3	Enabled 💌 40	≯ 40.1 ≯ 2840-3	2840-2 TV-G • 2840-3 TV-G •			
Show advanced contro	4	Enabled • 41	✓ App No settings		RF Channel Help		

General									
Power: 100-240 VAC 50/60 Hz, 60W max. 30W Typical IEC 60320-C14	Cooling: Dual internal cooling fans, Front inlet, Rear exhaust MBTF: 62,000 hours	Temperature/Humidity: Operating +32 F ⁰ to +113 F ⁰ (0 C ⁰ to +45 C ⁰) / 10% to 80%, non-condensing							
Compliance: FCC Class A, IEC60065, EN61000 (see manual 70-00031-00), CE, RoHS, RCM C-Tick	Enclosure Dimensions: 1.72 in. (H) x 17.33 in. (W) (without rack mount ears) x 9.9 in. (D) 43.6 mm (H) x 440.2 mm (W) x 251.5 mm (D)	Enclosure Type: Metal Shipping Weight: 6.25 lbs. (2.84 kg) Shipping Weight: 7.88 lbs. (3.58 kg)							
Mounting: Rack ears shipped attached, 1RU high	Carton Dimensions (individual): 4.25 in. (H) 30.875 in. W 12.125 in (D) 108 mm (H) 785 (mm) W 308 (mm) (D)	Warranty: 5 Years Vibration: NSTA 1A in carton							
Input									
HDMI: Four (4) ports per model up to 1080	Closed Caption: EIA/CEA-608 captions accepted over composite video input	Extra Digital Channel: MPEG2 Program stream file, up to 200 MB Encoder Audio Profile: ATSC A/52, (AC-3)							
tereo Analog andLine level input per channel DIN connectorigital Audio x4 or x2HDbridge end, RCA connector or digital SPDIF audio input. 3.5 mm pigtail connector with VGA									
Video Encoder									
Encoder Video Profile: MPEG2 HD: ISO13818-2 MainProfile@ HighLevel	Traffic Shaping: Variable Bit Rate	Video Encoding Data Rates: Variable, 10 Mbs – 24 Mbs per channel							
Average Encoding Data Rate: 18 Mbs per channel	Encoding Latency: Programmable 200 msec to 400 msec	Color Profile: 4:2:0							
GOP Size: 15	Video, Audio PID: Programmable starting value	Program Information: Programmable program name, EIT							
Modulator/Upverter									
Modulation Types: QAM 256 and 64 (ITU-T J83 Annex B) Interleaving modes: (64,2) only	Cable Standard: HRC, IRC or STD	Frequency Range: 4 paired, frequency agile QAM RF CATV Channels 2-135 • 2kHz resolution							
Output Power: +45 dBmV typical	Output Level Adjust: 25 – 45 dBmV in 1dBmV steps	• +/- 30 ppm accuracy • +/- 35 ppm stability							
I/Q Amplitude Imbalance: < 1% typical	Spectral Tilt: = 1 dB over 6 MHz typical</td <td>MER : > 38 dB typical</td>	MER : > 38 dB typical							
Control Setup									
Network Interface	10/100 Mb Ethernet via RJ45 connection IP address via DHCP or set by user HTML/Javascript served web interface for easy configuration Telnet connection for CLI scripting Easy firmware updates All settings saved in NV storage								
Front Panel Color Display	Quickly obtain status at a glance, basic configurations, software revisions and updates								

About ZeeVee

The company has revolutionized the pro AV and IT industries with its award-winning encoders, decoders and software. Integrators and AV consultants rely on ZeeVee for its reliability, excellent value and easy-to-install AV over IP and RF distribution platforms for enterprise, academic, government, healthcare, casino, museum, hospitality and retail customers. The company is a founding member of the SDVoE Alliance. It holds a GSA schedule and its products are TAA-compliant. ZeeVee is headquartered in greater Boston with its European head office in Augsburg, Germany and Southeast Asian offices in Singapore. For more information visit <u>www.zeevee.com</u>

ZeeVee products are TAA Compliant. ZeeVee holds GSA Contract # 47QTCA19D00JZ. REV20240228